

# 38226-MI

## Extra/Replacement Key FOB for Single Channel, Remote Control Relay

Extra/replacement Key FOB for 38225-RL Wireless Remote Control Relay.

**Key FOB Battery** CR2032 coin cell (Included)

**Frequency:** 433MHz

Temperature: -20° to +60°C

**L:** 2-3/8" **W:** 1-1/8" **T:** 1/2" **WT:** .07



**ADDITIONAL INFORMATION CAN BE FOUND ON  
THE 38225-RL DATA SHEET ONLINE AT MPJA.COM**

**SETUP: Requires the Relay Board  
to Code Match**

### Pairing to Module:

Press the pairing Button on the Relay Module (for about 2 seconds) Red LED will go off. Press Button on Key-FOB within 15sec. The code will be paired within the 15 seconds while the red light is off.

Code Reset: Press and Hold the pairing Button for 5 seconds, the LED indicator light flashes 4 times, and the code clearing was successful

PAIRING BUTTON

PAIRING LED



**MODULE NOT INCLUDED  
FOR ILLUSTRATION ONLY**

All Information including Drawings, Schematics etc, Referenced in this Document is supplied by MPJA inc. as a service to our customers. Accuracy or usefulness is not guaranteed nor is it an Endorsement of any particular part, supplier or manufacturer. Use of information and suitability for any application is at users own discretion and user assumes all risk.

Information Subject to Change Without Notice

All rights are retained by the respective Owners/Author(s)



**MARLIN P. JONES & ASSOC., INC.**

P.O. Box 530400 Lake Park, FL 33403

800-652-6733 FAX 561-844-8764

WWW.MPJA.COM